

AH1-SEN-PIR-SK

PIR and Daylight Sensor for Ace LED High Bay Fixtures (AH1)



The AH1-SEN-PIR-SK is a Plug & Play Passive Infrared and Daylight Sensor suitable for up to 40' Mounting Heights.

This Plug & Play sensor installs to Ace LED High Bays' (AH1) knockout. It provides automatic On/Off/Dim control based on motion and/or daylight levels. It uses PIR motion detector architecture and passive infrared (PIR) technology for improved detection coverage in high bay and low bay applications. Sensitivity, timers, and light levels can be adjusted with a remote programmer (SEN-PROG), sold separately.

TECHNICAL SPECIFICATIONS¹

- **Construction:** White Polycarbonate.
- **Sensing Technology:** Passive Infrared (PIR).
- **Connection Method:** 3-pin Screw-in.
- **Input Voltage:** 12-24V DC.
- **Current Consumption:** >50mA.
- **Standby Power:** ≤ 0.5W.
- **Control Output:** 0-10V, 25mA.
- **Operating Temperature Range:** -20°C to +60°C (-4°F to +140°F).
- **Max Mounting Height:** 40ft (12m).
- **Max Sensor Range:** 50ft (15m) radius.

LISTINGS

- FCC, UL, DLC, RoHS, IP65.

FEATURES

- Installs in seconds without tools or wiring.
- LED Motion Indicator.
- PIR Detection with 360° Coverage Pattern, best suited for areas with a clear line of sight.
- Integrated Daylight Sensor for Daylight Harvesting.
- Suitable for Indoor use.

CONTROL SETTINGS



- **Sensitivity (Detection Area):** 25%/50%/75%/100%.
- **Hold Time:** 10s/1min/5min/10min/15min/20min/30min/60min.
- **Daylight Threshold On:** 10lux/30lux/50lux/current value.
- **Daylight Threshold Off:** 100lux/300lux/500lux/disabled.
- **Stand-by Time:** 1min/30min/60min/+∞.
- **Stand-by Dim Level:** 0%/10%/30%/50%.



ORDERING

Part Number	Description
AH1-SEN-PIR-SK	PIR Occupancy and Daylight Sensor, 3-pin Screw-in System, Plug & Play, On/Off/Dim, 40' Max Mounting Height. Field installed, for Ace LED High Bays (AH1) fixtures. Sensor can be re-programmed on the field with remote SEN-PROG (sold separately).
SEN-PROG	Infrared Remote Programmer. Required to change default settings and modes of operation.

SENSOR COVERAGE



SENSOR OPERATION

On/Off/Dim (Default Mode)

Factory default settings: Sensitivity: 100%, Hold time: 5min, Daylight sensor: disabled, Stand-by dim level: 30%, Stand-by time: 60min. This mode offers three levels of light: On/Off/Dim and two periods of selectable waiting time: Hold Time and Stand-by Time.



With sufficient natural light, even when motion is detected, the fixture remains **Off**.



With insufficient natural light, when motion is detected, the fixture turns **On**.




After hold time, the fixture **Dims** to stand-by level if natural light stays below daylight threshold.




The fixture switches **Off** automatically after the stand-by time.

Smart Daylight Control


Enable the smart daylight sensor functionality by pushing  when the remote programmer is in settings mode.



The fixture turns **On** at 100% when motion is detected.





The fixture **Dims** to stand-by level after hold time.




The fixture remains **Dimmed** to stand-by level at night.

Settings for this example:


- Hold Time: 30min
- Daylight Threshold On: 50lux
- Daylight Threshold Off: 300lux
- Stand-by Dim Level: 10%
- Stand-by Time: ∞
(when the smart photocell sensor open, stand-by period is only ∞)



When natural light exceeds the daylight threshold off, the fixture will turn **Off** even if motion is detected.




The fixture automatically turns **On** at 10% stand-by dim level when natural light is insufficient (no motion).



INFRARED REMOTE PROGRAMMER

The Infrared Remote Programmer (SEN-PROG) is required to change default settings and modes of operation.



Specifications

Power Supply	2 x AAA 1.5V batteries.
Upload Range	Up to 50 ft.
Op. Temperature	0°C to 50°C (32°F to 122°F).

LED Indicators

Brightness	Light output during occupancy.
Sensitivity	Detection area of the sensor.
Hold Time	Time the sensor waits to turn off or dim the light after the area is vacated.
Daylight Sensor	Daylight sensor status and daylight threshold values in lux.
	Daylight harvesting function. Selects the current surrounding lux value as the daylight threshold.
	Daylight sensor disabled. All motion detected turns on the light, no matter how bright the natural light is.
Stand-by Dim	Light output during vacancy.
Stand-by Time	Time the sensor keeps the light at stand-by dim level after the hold time has elapsed.


Scene Modes

The remote comes with four pre-programmed modes. These can be used as is, or adjusted with different parameters and saved over an existing mode.


Scene	Application	Brightness	Sensitivity	Hold Time	Stand-by Dim	Stand-by Time	Daylight Sensor
MODE 1	Indoor	100%	75%	5min	30%	30min	Disabled
MODE 2	Indoor	100%	75%	1min	30%	+∞	Disabled
MODE 3	Indoor	100%	75%	5min	30%	30min	30lux
MODE 4	Outdoor	100%	75%	1min	30%	+∞	30lux/300lux

DIMENSIONS & DRAWINGS

Sensor



Receptacle



Drawings not to scale

FOOTNOTES

1. The performance of sensors and lenses is influenced by various factors beyond Linmore's control, including but not limited to environmental conditions, user settings, and proper maintenance. While we provide detailed specifications and guidelines to help optimize performance, we cannot guarantee or be held liable for the performance of sensors or lenses under any particular circumstance(s). Customers are advised to test the products in their specific application environments to ensure suitability for their intended use and are responsible for all sensor and lens selections.

Updated: 2026/10/07

Linmore

2360 S Orange Ave, Fresno, CA 93725 | 559 485 6010 | info@linmoreled.com | linmoreled.com

 **Linmore**

All specifications are subject to change without notice. Please visit linmoreled.com for latest information. All values are typical or design values. Actual performance may differ as a result of end-user environments and applications. Consult Linmore with specific inquiries. Copyright © 2026, Linmore. All rights reserved.